

G59/3 TYPE TEST VERIFICATION REPORT

<p>This Type Test sheet shall be used to record the results of the type testing of Generating Unit between 16A per phase and 17kW per phase maximum output at 230V (17kW limit single phase, 34kW limit split phase, 50kW limit 3 phase) It includes the Generating Units supplier declaration of compliance with the requirements of Engineering Recommendation G59/3</p>			
Type Tested reference number		X3-30.0-T/X3-36.0-T	
Generating Unit technology		Photovoltaic Grid-tied inverter	
System supplier name		Solax power Co., Ltd	
Address		Room 220, West Buliding A, National University Science and Technology Park of Zhejiang University 525, Xixi Rd, Hangzhou, Zhejiang Province, China, 310007	
Tel	+86(0571)-56260011	Fax	+86(0571)-56075753
E:mail	info@soalxpower.com	Web site	www.solaxpower.com
Maximum export capacity, use separate sheet if more than one connection option.	30.0	kW three phase	
	36.0	kW three phase	
	NA	kW single phase	
	NA	kW two phases in three phase system	
	NA	kW two phases split phase system	
<p>System supplier declaration. - I certify on behalf of the company named above as a supplier of a Generating Unit, that all products supplied by the company with the above Type Test reference number will be manufactured and tested to ensure that they perform as stated in this document, prior to shipment to site and that no site modifications are required to ensure that the product meets all the requirements of G59/3.</p>			
Signed	<i>Guo Huawei</i>	On behalf of	Solax power Co., Ltd
<p>Note that testing can be done by the manufacturer of an individual component, by an external test house, or by the supplier of the complete system, or any combination of them as appropriate. Where parts of the testing are carried out by persons or organisations other than the supplier then the supplier shall keep copies of all test records and results supplied to them to verify that the testing has been carried out by people with sufficient technical competency to carry out the tests.</p>			

Power Quality. Harmonics. These tests should be carried out as specified in 61000-3-12 or 61000-3-2. Only one set of tests is required and the **Manufacturer** should decide which one to use and complete the relevant table. The chosen test should be undertaken with a fixed source of energy at two power levels a) between 45 and 55% and b) at 100% of maximum export capacity. The test should be carried out on a single **Generating Unit**. The results need to comply with the limits of table 2 of BS EN 61000-3-12 for single phase equipment, to table 3 of BS EN 61000-3-12 for three phase equipment or to table 1 of BS EN 61000-3-2 if that standard is used. Note that Generating Units meeting the requirements of BS EN 61000-3-2 will need no further assessment with regards to harmonics. Generating Units with emissions close to the limits laid down in BS EN 61000-3-12 may require the installation of a transformer between 2 and 4 times the rating of the **Generating Unit** in order to accept the connection to a **DNO's** network.

Generating Unit tested to BS EN 61000-3-12

X3-36.0-T (L1)

Generating Unit rating per phase (rpp)		12.0	kVA		Harmonic % =Measured Value (Amps) x 23/rating per phase (kVA)	
Harmonic	At 45-55% of rated output		100% of rated output		Limit in BS EN 61000-3-12	
	Measured Value MV in Amps	%	Measured Value MV in Amps	%	1 phase	3 phase
2	0.109	0.209	0.137	0.263	8%	8%
3	0.135	0.259	0.097	0.186	21.6	Not stated
4	0.085	0.163	0.098	0.188	4%	4%
5	0.171	0.328	0.148	0.284	10.7%	10.7%
6	0.036	0.069	0.036	0.069	2.67%	2.67%
7	0.176	0.337	0.187	0.358	7.2%	7.2%
8	0.024	0.046	0.032	0.061	2%	2%
9	0.034	0.065	0.059	0.113	3.8%	Not stated
10	0.036	0.069	0.034	0.065	1.6%	1.6%
11	0.142	0.272	0.124	0.238	3.1%	3.1%
12	0.028	0.054	0.024	0.046	1.33%	1.33%
13	0.129	0.247	0.122	0.234	2%	2%
THD		1.479		0.784	23%	13%
PWHD					23%	22%

Power Quality. Harmonics. These tests should be carried out as specified in 61000-3-12 or 61000-3-2. Only one set of tests is required and the **Manufacturer** should decide which one to use and complete the relevant table. The chosen test should be undertaken with a fixed source of energy at two power levels a) between 45 and 55% and b) at 100% of maximum export capacity. The test should be carried out on a single **Generating Unit**. The results need to comply with the limits of table 2 of BS EN 61000-3-12 for single phase equipment, to table 3 of BS EN 61000-3-12 for three phase equipment or to table 1 of BS EN 61000-3-2 if that standard is used. Note that Generating Units meeting the requirements of BS EN 61000-3-2 will need no further assessment with regards to harmonics. Generating Units with emissions close to the limits laid down in BS EN 61000-3-12 may require the installation of a transformer between 2 and 4 times the rating of the **Generating Unit** in order to accept the connection to a **DNO's** network.

Generating Unit tested to BS EN 61000-3-12

X3-36.0-T (L2)

Generating Unit rating per phase (rpp)		12.0	kVA		Harmonic % =Measured Value (Amps) x 23/rating per phase (kVA)	
Harmonic	At 45-55% of rated output		100% of rated output		Limit in BS EN 61000-3-12	
	Measured Value MV in Amps	%	Measured Value MV in Amps	%	1 phase	3 phase
2	0.135	0.259	0.158	0.303	8%	8%
3	0.108	0.207	0.109	0.209	21.6	Not stated
4	0.089	0.171	0.091	0.174	4%	4%
5	0.206	0.395	0.2	0.383	10.7%	10.7%
6	0.026	0.050	0.014	0.027	2.67%	2.67%
7	0.158	0.303	0.177	0.339	7.2%	7.2%
8	0.031	0.059	0.036	0.069	2%	2%
9	0.025	0.048	0.035	0.067	3.8%	Not stated
10	0.013	0.025	0.013	0.025	1.6%	1.6%
11	0.145	0.278	0.126	0.242	3.1%	3.1%
12	0.026	0.050	0.025	0.048	1.33%	1.33%
13	0.129	0.247	0.128	0.245	2%	2%
THD		1.534		0.866	23%	13%
PWHD					23%	22%

Power Quality. Harmonics. These tests should be carried out as specified in 61000-3-12 or 61000-3-2. Only one set of tests is required and the **Manufacturer** should decide which one to use and complete the relevant table. The chosen test should be undertaken with a fixed source of energy at two power levels a) between 45 and 55% and b) at 100% of maximum export capacity. The test should be carried out on a single **Generating Unit**. The results need to comply with the limits of table 2 of BS EN 61000-3-12 for single phase equipment, to table 3 of BS EN 61000-3-12 for three phase equipment or to table 1 of BS EN 61000-3-2 if that standard is used. Note that Generating Units meeting the requirements of BS EN 61000-3-2 will need no further assessment with regards to harmonics. Generating Units with emissions close to the limits laid down in BS EN 61000-3-12 may require the installation of a transformer between 2 and 4 times the rating of the **Generating Unit** in order to accept the connection to a **DNO's** network.

Generating Unit tested to BS EN 61000-3-12

X3-36.0-T (L3)

Generating Unit rating per phase (rpp)		12.0	kVA		Harmonic % =Measured Value (Amps) x 23/rating per phase (kVA)	
Harmonic	At 45-55% of rated output		100% of rated output		Limit in BS EN 61000-3-12	
	Measured Value MV in Amps	%	Measured Value MV in Amps	%	1 phase	3 phase
2	0.105	0.201	0.144	0.276	8%	8%
3	0.206	0.395	0.217	0.416	21.6	Not stated
4	0.094	0.180	0.125	0.240	4%	4%
5	0.178	0.341	0.147	0.282	10.7%	10.7%
6	0.029	0.056	0.041	0.079	2.67%	2.67%
7	0.16	0.307	0.178	0.341	7.2%	7.2%
8	0.03	0.058	0.048	0.092	2%	2%
9	0.033	0.063	0.064	0.123	3.8%	Not stated
10	0.034	0.065	0.032	0.061	1.6%	1.6%
11	0.141	0.270	0.122	0.234	3.1%	3.1%
12	0.026	0.050	0.03	0.058	1.33%	1.33%
13	0.131	0.251	0.123	0.236	2%	2%
THD		1.682		0.866	23%	13%
PWHD					23%	22%

Power Quality. Harmonics. These tests should be carried out as specified in 61000-3-12 or 61000-3-2. Only one set of tests is required and the **Manufacturer** should decide which one to use and complete the relevant table. The chosen test should be undertaken with a fixed source of energy at two power levels a) between 45 and 55% and b) at 100% of maximum export capacity. The test should be carried out on a single **Generating Unit**. The results need to comply with the limits of table 2 of BS EN 61000-3-12 for single phase equipment, to table 3 of BS EN 61000-3-12 for three phase equipment or to table 1 of BS EN 61000-3-2 if that standard is used. Note that Generating Units meeting the requirements of BS EN 61000-3-2 will need no further assessment with regards to harmonics. Generating Units with emissions close to the limits laid down in BS EN 61000-3-12 may require the installation of a transformer between 2 and 4 times the rating of the **Generating Unit** in order to accept the connection to a **DNO's** network.

Generating Unit tested to BS EN 61000-3-12

X3-30.0-T (L1)

Generating Unit rating per phase (rpp)		10.0	kVA		Harmonic % =Measured Value (Amps) x 23/rating per phase (kVA)	
Harmonic	At 45-55% of rated output		100% of rated output		Limit in BS EN 61000-3-12	
	Measured Value MV in Amps	%	Measured Value MV in Amps	%	1 phase	3 phase
2	0.096	0.221	0.131	0.301	8%	8%
3	0.116	0.267	0.101	0.232	21.6	Not stated
4	0.071	0.163	0.096	0.221	4%	4%
5	0.159	0.366	0.162	0.373	10.7%	10.7%
6	0.033	0.076	0.03	0.069	2.67%	2.67%
7	0.162	0.373	0.175	0.403	7.2%	7.2%
8	0.022	0.051	0.028	0.064	2%	2%
9	0.02	0.046	0.031	0.071	3.8%	Not stated
10	0.032	0.074	0.023	0.053	1.6%	1.6%
11	0.131	0.301	0.128	0.294	3.1%	3.1%
12	0.024	0.055	0.024	0.055	1.33%	1.33%
13	0.119	0.274	0.12	0.276	2%	2%
THD		1.366		0.788	23%	13%
PWHD					23%	22%

Power Quality. Harmonics. These tests should be carried out as specified in 61000-3-12 or 61000-3-2. Only one set of tests is required and the **Manufacturer** should decide which one to use and complete the relevant table. The chosen test should be undertaken with a fixed source of energy at two power levels a) between 45 and 55% and b) at 100% of maximum export capacity. The test should be carried out on a single **Generating Unit**. The results need to comply with the limits of table 2 of BS EN 61000-3-12 for single phase equipment, to table 3 of BS EN 61000-3-12 for three phase equipment or to table 1 of BS EN 61000-3-2 if that standard is used. Note that Generating Units meeting the requirements of BS EN 61000-3-2 will need no further assesment with regards to harmonics. Generating Units with emissions close to the limits laid down in BS EN 61000-3-12 may require the installation of a transformer between 2 and 4 times the rating of the **Generating Unit** in order to accept the connection to a **DNO's** network.

Generating Unit tested to BS EN 61000-3-12

X3-30.0-T (L2)

Generating Unit rating per phase (rpp)		10.0	kVA		Harmonic % =Measured Value (Amps) x 23/rating per phase (kVA)	
Harmonic	At 45-55% of rated output	100% of rated output			Limit in BS EN 61000-3-12	
	Measured Value MV in Amps	%	Measured Value MV in Amps	%	1 phase	3 phase
2	0.112	0.258	0.145	0.334	8%	8%
3	0.093	0.214	0.088	0.202	21.6	Not stated
4	0.074	0.170	0.085	0.196	4%	4%
5	0.188	0.432	0.186	0.428	10.7%	10.7%
6	0.023	0.053	0.029	0.067	2.67%	2.67%
7	0.149	0.343	0.158	0.363	7.2%	7.2%
8	0.029	0.067	0.036	0.083	2%	2%
9	0.024	0.055	0.032	0.074	3.8%	Not stated
10	0.028	0.064	0.024	0.055	1.6%	1.6%
11	0.137	0.315	0.126	0.290	3.1%	3.1%
12	0.023	0.053	0.022	0.051	1.33%	1.33%
13	0.121	0.278	0.11	0.253	2%	2%
THD		1.403		0.779	23%	13%
PWHD					23%	22%

Power Quality. Harmonics. These tests should be carried out as specified in 61000-3-12 or 61000-3-2. Only one set of tests is required and the **Manufacturer** should decide which one to use and complete the relevant table. The chosen test should be undertaken with a fixed source of energy at two power levels a) between 45 and 55% and b) at 100% of maximum export capacity. The test should be carried out on a single **Generating Unit**. The results need to comply with the limits of table 2 of BS EN 61000-3-12 for single phase equipment, to table 3 of BS EN 61000-3-12 for three phase equipment or to table 1 of BS EN 61000-3-2 if that standard is used. Note that Generating Units meeting the requirements of BS EN 61000-3-2 will need no further assesment with regards to harmonics. Generating Units with emissions close to the limits laid down in BS EN 61000-3-12 may require the installation of a transformer between 2 and 4 times the rating of the **Generating Unit** in order to accept the connection to a **DNO's** network.

Generating Unit tested to BS EN 61000-3-12

X3-30.0-T (L3)

Generating Unit rating per phase (rpp)		10.0	kVA		Harmonic % =Measured Value (Amps) x 23/rating per phase (kVA)	
Harmonic	At 45-55% of rated output		100% of rated output		Limit in BS EN 61000-3-12	
	Measured Value MV in Amps	%	Measured Value MV in Amps	%	1 phase	3 phase
2	0.11	0.253	0.143	0.329	8%	8%
3	0.211	0.485	0.191	0.439	21.6	Not stated
4	0.08	0.184	0.102	0.235	4%	4%
5	0.158	0.363	0.143	0.329	10.7%	10.7%
6	0.032	0.074	0.037	0.085	2.67%	2.67%
7	0.147	0.338	0.164	0.377	7.2%	7.2%
8	0.028	0.064	0.044	0.101	2%	2%
9	0.031	0.071	0.03	0.069	3.8%	Not stated
10	0.029	0.067	0.033	0.076	1.6%	1.6%
11	0.133	0.306	0.121	0.278	3.1%	3.1%
12	0.028	0.064	0.028	0.064	1.33%	1.33%
13	0.123	0.283	0.116	0.267	2%	2%
THD		1.535		0.812	23%	13%
PWHD					23%	22%

Power Quality. Voltage fluctuations and Flicker. The tests should be carried out on a single **Generating Unit**. Results should be normalised to a standard source impedance or if this results in figures above the limits set in BS EN 61000-3-11 to a suitable Maximum Impedance.

X3-36.0-T/ X3-30.0-T

\	Starting			Stopping			Running	
	d _{max}	d _c	d _(t)	d _{max}	d _c	d _(t)	P _{st}	P _{lt} 2 hours
Measured Values at test impedance	0.52%	0.16%	0%	0.72%	0.13%	0%	0.68	0.64
Normalised to standard impedance								
Normalised to required maximum impedance								
Limits set under BS EN 61000-3-11	4%	3.3%	3.3%	4%	3.3%	3.3%	1.0	0.65
Test Impedance	R	0.4	Ω	XI	0.25	Ω		
Standard Impedance	R	0.24 * 0.4 ^	Ω	XI	0.15 * 0.25 ^	Ω		
Maximum Impedance	R		Ω	XI		Ω		

* Applies to three phase and split single phase Generating Units

^ Applies to single phase Generating Units and Generating Units using two phases on a three phase system

For voltage change and flicker measurements the following formula is to be used to convert the measured values to the normalised values where the power factor of the generation output is 0.98 or above.

Normalised value = Measured value*reference source resistance/measured source resistance at test point

Single phase units reference source resistance is 0.4 Ω

Two phase units in a three phase system reference source resistance is 0.4 Ω

Two phase units in a split phase system reference source resistance is 0.24 Ω

Three phase units reference source resistance is 0.24 Ω

Where the power factor of the output is under 0.98 then the XI to R ratio of the test impedance should be close to that of the Standard Impedance.

The stopping test should be a trip from full load operation.

The duration of these tests need to comply with the particular requirements set out in the testing notes for the technology under test. Dates and location of the test need to be noted below

Test start date	2017-04-27	Test end date	2017-04-27
Test location	No.99, Wenlan Road, Qixia, Nanjing		

Power quality. DC injection. The tests should be carried out on a single **Generating Unit**
 Tests are to be carried out three power defined levels $\pm 5\%$. At 230V a 2kW single phase inverter has a current output of 8.7A so DC limit is 21.75mA, a 10kW three phase inverter has a current output of 43.5A at 230V so DC limit is 108.75mA

X3-36.0-T (L1)

Test power level	10%	55%	100%	
Recorded value in Amps	0.054	0.066	0.078	
as % of rated AC current	0.12%	0.14%	0.17%	
Limit	0.25%	0.25%	0.25%	

Power quality. DC injection. The tests should be carried out on a single **Generating Unit**
 Tests are to be carried out three power defined levels $\pm 5\%$. At 230V a 2kW single phase inverter has a current output of 8.7A so DC limit is 21.75mA, a 10kW three phase inverter has a current output of 43.5A at 230V so DC limit is 108.75mA

X3-36.0-T (L2)

Test power level	10%	55%	100%	
Recorded value in Amps	0.055	0.080	0.093	
as % of rated AC current	0.12%	0.17%	0.2%	
Limit	0.25%	0.25%	0.25%	

Power quality. DC injection. The tests should be carried out on a single **Generating Unit**
 Tests are to be carried out three power defined levels $\pm 5\%$. At 230V a 2kW single phase inverter has a current output of 8.7A so DC limit is 21.75mA, a 10kW three phase inverter has a current output of 43.5A at 230V so DC limit is 108.75mA

X3-36.0-T (L3)

Test power level	10%	55%	100%	
Recorded value in Amps	0.028	0.032	0.058	
as % of rated AC current	0.06%	0.07%	0.12%	
Limit	0.25%	0.25%	0.25%	

Power quality. DC injection. The tests should be carried out on a single **Generating Unit**
 Tests are to be carried out three power defined levels $\pm 5\%$. At 230V a 2kW single phase inverter has a current output of 8.7A so DC limit is 21.75mA, a 10kW three phase inverter has a current output of 43.5A at 230V so DC limit is 108.75mA

X3-30.0-T (L1)

Test power level	10%	55%	100%	
Recorded value in Amps	0.108	0.063	0.074	
as % of rated AC current	0.24%	0.14%	0.16%	
Limit	0.25%	0.25%	0.25%	

Power quality. DC injection. The tests should be carried out on a single **Generating Unit**
 Tests are to be carried out three power defined levels $\pm 5\%$. At 230V a 2kW single phase inverter has a current output of 8.7A so DC limit is 21.75mA, a 10kW three phase inverter has a current output of 43.5A at 230V so DC limit is 108.75mA

X3-30.0-T (L2)

Test power level	10%	55%	100%	
Recorded value in Amps	0.09	0.078	0.083	
as % of rated AC current	0.2%	0.17%	0.18%	
Limit	0.25%	0.25%	0.25%	

Power quality. DC injection. The tests should be carried out on a single **Generating Unit**
 Tests are to be carried out three power defined levels $\pm 5\%$. At 230V a 2kW single phase inverter has a current output of 8.7A so DC limit is 21.75mA, a 10kW three phase inverter has a current output of 43.5A at 230V so DC limit is 108.75mA

X3-30.0-T (L3)

Test power level	10%	55%	100%	
Recorded value in Amps	0.34	0.028	0.042	
as % of rated AC current	0.07%	0.06%	0.09%	
Limit	0.25%	0.25%	0.25%	

Power Quality. Power factor. The tests should be carried out on a single **Generating Unit**.
 Tests are to be carried out at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.

X3-36.0-T (L1)

	260.3V	277V	304.7V	Measured at three voltage levels and at full output. Voltage to be
Measured	0.999	0.999	0.999	

value				maintained within + or – 1.5% of the stated level during the test.
Limit	>0.95	>0.95	>0.95	
<p>Power Quality. Power factor. The tests should be carried out on a single Generating Unit. Tests are to be carried out at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.</p>				
X3-36.0-T (L2)				
	260.3V	277V	304.7V	Measured at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.
Measured value	0.999	0.999	0.999	
Limit	>0.95	>0.95	>0.95	

<p>Power Quality. Power factor. The tests should be carried out on a single Generating Unit. Tests are to be carried out at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.</p>				
X3-36.0-T (L3)				
	260.3V	277V	304.7V	Measured at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.
Measured value	0.999	0.999	0.999	
Limit	>0.95	>0.95	>0.95	

<p>Power Quality. Power factor. The tests should be carried out on a single Generating Unit. Tests are to be carried out at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.</p>				
X3-30.0-T (L1)				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.
Measured value	0.999	0.999	0.999	
Limit	>0.95	>0.95	>0.95	

<p>Power Quality. Power factor. The tests should be carried out on a single Generating Unit. Tests are to be carried out at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.</p>				
X3-30.0-T (L2)				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the
Measured value	0.999	0.999	0.999	

Limit	>0.95	>0.95	>0.95	stated level during the test.
-------	-------	-------	-------	-------------------------------

Power Quality. Power factor. The tests should be carried out on a single Generating Unit. Tests are to be carried out at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.

X3-30.0-T (L3)				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.
Measured value	0.999	0.999	0.999	
Limit	>0.95	>0.95	>0.95	

Protection. Frequency tests(X3-36.0-T)

Function	Setting		Trip test		“No-trip tests”	
	Frequency	Time delay	Frequency	Time delay	Frequency /time	Confirm no trip
O/F stage 1	51.5Hz	90s	51.52Hz	91s	51.3Hz 95s	No trip
O/F stage 2	52Hz	0.5s	52.01Hz	0.514s	51.8Hz 89.98s	No trip
					52.2Hz 0.48s	No trip
U/F stage 1	47.5Hz	20s	47.49Hz	20.3s	47.7Hz 25s	No trip
U/F stage 2	47Hz	0.5s	46.99Hz	0.548s	47.2Hz 19.98s	No trip
					46.8 Hz 0.48s	No trip

Note. For frequency Trip tests the Frequency required to trip is the setting ± 0.1Hz. In order to measure the time delay a larger deviation than the minimum required to operate the projection can be used.. The “No-trip tests” need to be carried out at the setting ± 0.2Hz and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

Protection. Frequency tests(X3-30.0-T)

Function	Setting		Trip test		“No-trip tests”	
	Frequency	Time delay	Frequency	Time delay	Frequency /time	Confirm no trip

O/F stage 1	51.5Hz	90s	51.52Hz	90.6s	51.3Hz 95s	No trip
O/F stage 2	52Hz	0.5s	52.01Hz	0.766s	51.8Hz 89.98s	No trip
					52.2Hz 0.48s	No trip
U/F stage 1	47.5Hz	20s	47.49Hz	20.4s	47.7Hz 25s	No trip
U/F stage 2	47Hz	0.5s	46.99Hz	0.514s	47.2Hz 19.98s	No trip
					46.8 Hz 0.48s	No trip

Note. For frequency Trip tests the Frequency required to trip is the setting $\pm 0.1\text{Hz}$. In order to measure the time delay a larger deviation than the minimum required to operate the projection can be used.. The “No-trip tests” need to be carried out at the setting $\pm 0.2\text{Hz}$ and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

Protection. Voltage tests (X3-36.0-T)

Function	Setting		Trip test		“No trip-tests” All phases at same voltage	
	Voltage	Time delay	Voltage	Time delay	Voltage /time	Confirm no trip
O/V stage 1	315.7V	1.0s	315.7V	1.130s	310.9V 2.0 sec	No trip
O/V stage 2	329.6V	0.5s	329.6V	0.638s	324.8V 0.98s	No trip
					334.4V 0.48s	No trip
U/V stage 1	240.9V	2.5s	240.3V	2.64s	245.8V 3.5s	No trip
U/V stage 2	221.6V	0.5s	221.5V	0.612s	226.4V 2.46s	No trip
					216.7v 0.52 sec	No trip

Note. For voltage tests the voltage required to trip is the setting plus or minus 3.45V. The time delay can be measured at a larger deviation than the minimum required to operate the projection. The No-trip tests need to be carried out at the setting $\pm 4\text{V}$ and for the relevant

times as shown in the table above to ensure that the protection will not trip in error.

Protection. Voltage tests (X3-30.0-T)						
Function	Setting		Trip test		"No trip-tests" All phases at same voltage	
	Voltage	Time delay	Voltage	Time delay	Voltage /time	Confirm no trip
O/V stage 1	262.2V	1.0s	261.9V	1.17s	258.2V 2.0 sec	No trip
O/V stage 2	273.7V	0.5s	272.8V	0.762s	324.8V 0.98s	No trip
					277.7V 0.48s	No trip
U/V stage 1	200.1V	2.5s	199.4V	2.65s	204.1V 3.5s	No trip
U/V stage 2	184V	0.5s	183.4V	0.566s	188V 2.46s	No trip
					180v 0.52 sec	No trip

Note. For voltage tests the voltage required to trip is the setting plus or minus 3.45V. The time delay can be measured at a larger deviation than the minimum required to operate the projection. The No-trip tests need to be carried out at the setting $\pm 4V$ and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

a) Protection. Loss of Mains test and single phase test. The tests are to be carried out at three output power levels plus or minus 5%, an alternative for inverter connected Generating Units can be used instead.

Note as an alternative, inverters can be tested to BS EN 62116. The following sub set of tests should be recorded in the following table.

X3-36.0-T/ X3-30.0-T						
Test Power and imbalance	33% -5% Q Test 22	66% -5% Q Test 12	100% -5% P Test 5	33% +5% Q Test 31	66% +5% Q Test 21	100% +5% P Test 10
Trip time. Limit is 0.5s	0.024s	0.015s	0.080s	0.016s	0.030s	0.079s

a) Protection. Frequency change, Stability test				
X3-36.0-T/ X3-30.0-T				
	Start Frequency	Change	End Frequency	Confirm no trip
Positive Vector Shift	49.5Hz	+9 degrees		No trip
Negative Vector Shift	50.5Hz	- 9 degrees		No trip
Positive Frequency drift	49.5Hz	+0.19Hzs ⁻¹	51.5Hz	No trip
Negative Frequency drift	50.5Hz	-0.19Hzs ⁻¹	47.5Hz	No trip

a) Protection. Re-connection timer. The tests should prove that the reconnection sequence starts in no less than 20s for restoration of voltage and frequency to within the stage 1 settings of table 10.5.7.1 (X3-36.0-T)					
Test should prove that the reconnection sequence starts in no less than 20s for restoration of voltage and frequency to within the stage 1 settings of table 10.5.7.1					
Time delay setting (s)	Measured delay (s)	Checks on no reconnection when voltage or frequency is brought to just outside stage 1 limits of table 10.5.7.1.			
60	80.8s	At 320.5V	At 236.1V	At 47.4Hz	At 51.6Hz
Confirmation that the Generating Unit does not re-connect		No re-connection	No re-connection	No re-connection	No re-connection

b) Protection. Re-connection timer. The tests should prove that the reconnection sequence starts in no less than 20s for restoration of voltage and frequency to within the stage 1 settings of table 10.5.7.1 (X3-30.0-T)					
Test should prove that the reconnection sequence starts in no less than 20s for restoration of voltage and frequency to within the stage 1 settings of table 10.5.7.1					
Time delay setting (s)	Measured delay (s)	Checks on no reconnection when voltage or frequency is brought to just outside stage 1 limits of table 10.5.7.1.			
60	68.25s	At 266.2V	At 196.1V	At 47.4Hz	At 51.6Hz
Confirmation that the Generating Unit does not re-connect		No re-connection	No re-connection	No re-connection	No re-connection

d) Fault level contribution					
For machines with electro-magnetic output			For Inverter output		
Parameter	Symbol	Value	Time after fault	Volts	Amps
Peak Short Circuit current	i_p		20ms	50.5	57.1
Initial Value of aperiodic current	A		100ms	50.2	40
Initial symmetrical short-circuit current*	I_k		250ms	50.4	25.4
Decaying (aperiodic) component of short circuit current*	i_{DC}		500ms	50.1	18.1
Reactance/Resistance Ratio of source*	X/R		Time to trip	0.049s	In seconds

For rotating machines and linear piston machines the test should produce a 0s – 2s plot of the short circuit current as seen at the **Generating Unit** terminals.

* Values for these parameters should be provided where the short circuit duration is sufficiently long to enable interpolation of the plot

b) Self Monitoring solid state switching	Yes/NA
It has been verified that in the event of the solid state switching device failing to disconnect the Generating Unit , the voltage on the output side of the switching device is reduced to a value below 50 Volts within 0.5 seconds	NA

Additional comments