



G83/2 Appendix 4 Type Verification Test Report

Type Approval and manufacturer/supplier declaration of compliance with the requirements of Engineering Recommendation G83/2.			
SSEG Type reference number		Photovoltaic Grid-tied inverter	
SSEG Type		X3-Hybrid-5.0-N-C; X3-Hybrid-5.0-D-C X3-Hybrid-5.0-N-E; X3-Hybrid-5.0-D-E X3-Hybrid-6.0-N-C; X3-Hybrid-6.0-D-C X3-Hybrid-6.0-N-E; X3-Hybrid-6.0-D-E X3-Hybrid-8.0-N-C; X3-Hybrid-8.0-D-C X3-Hybrid-8.0-N-E; X3-Hybrid-8.0-D-E X3-Hybrid-10.0-N-C; X3-Hybrid-10.0-D-C X3-Hybrid-10.0-N-E; X3-Hybrid-10.0-D-E X3-Fit-8.0E; X3-Fit-8.0C X3-Fit-10.0E; X3-Fit-10.0C	
System Supplier name		SolaX Power Network Technology(Zhe jiang) Co., Ltd.	
Address		Room 220, West Buliding A, National University Science and Technology Park of Zhejiang University 525, Xixi Rd, Hangzhou, Zhejiang Province, China, 310007	
Tel	+86(0571)-56260011	Fax	+86(0571)-56075753
E:mail	info@soalxpower.com	Web site	www.solaxpower.com
Maximum rated capacity, use separate sheet if more than one connection option.	Connection Option		
	5.0	kW three phase system	
	6.0	kW three phase system	
	8.0	kW three phase system	
10.0	kW three phase system		
SSEG manufacturer/supplier declaration. I certify on behalf of the company named above as a manufacturer/supplier of Small Scale Embedded Generators, that all products manufactured/supplied by the company with the above SSEG Type reference number will be manufactured and tested to ensure that they perform as stated in this Type Verification Test Report, prior to shipment to site and that no site modifications are required to ensure that the product meets all the requirements of G83/2.			
Signed	<i>Guo Huawei</i>	On behalf of	SolaX Power Network Technology (Zhe jiang) Co., Ltd.
<p>Note that testing can be done by the manufacturer of an individual component, by an external test house, or by the supplier of the complete system, or any combination of them as appropriate. Where parts of the testing are carried out by persons or organisations other than the supplier then the supplier shall keep copies of all test records and results supplied to them to verify that the testing has been carried out by people with sufficient technical competency to carry out the tests.</p>			



Power Quality. Harmonics. The requirement is specified in section 5.4.1, test procedure in Annex A or B 1.4.1								
SSEG rating per phase (rpp)				5.0/3=1.66 kW			NV=MV*3.68/rpp	
Harmonic	At 50% of rated output						Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps		
2	0.019	0.042	0.024	0.053	0.029	0.064	1.080	
3	0.082	0.181	0.081	0.179	0.075	0.166	2.300	
4	0.003	0.007	0.004	0.009	0.007	0.015	0.430	
5	0.034	0.075	0.036	0.079	0.040	0.088	1.140	
6	0.005	0.011	0.005	0.011	0.005	0.011	0.300	
7	0.032	0.071	0.029	0.064	0.033	0.073	0.770	
8	0.005	0.011	0.005	0.011	0.006	0.013	0.230	
9	0.020	0.044	0.019	0.042	0.023	0.051	0.400	
10	0.007	0.015	0.006	0.013	0.005	0.011	0.184	
11	0.019	0.042	0.019	0.042	0.023	0.051	0.330	
12	0.003	0.007	0.002	0.004	0.003	0.007	0.153	
13	0.016	0.035	0.016	0.035	0.015	0.033	0.210	
14	0.004	0.009	0.004	0.009	0.005	0.011	0.131	
15	0.012	0.026	0.012	0.026	0.017	0.038	0.150	
16	0.003	0.007	0.005	0.011	0.004	0.009	0.115	
17	0.012	0.026	0.013	0.029	0.013	0.029	0.132	
18	0.004	0.009	0.004	0.009	0.004	0.009	0.102	
19	0.011	0.024	0.012	0.026	0.014	0.031	0.118	
20	0.013	0.029	0.011	0.024	0.013	0.029	0.092	
21	0.019	0.042	0.019	0.042	0.019	0.042	0.107	0.160
22	0.012	0.026	0.010	0.022	0.012	0.026	0.084	
23	0.022	0.049	0.020	0.044	0.023	0.051	0.098	0.147
24	0.006	0.013	0.006	0.013	0.008	0.018	0.077	
25	0.010	0.022	0.011	0.024	0.011	0.024	0.090	0.135
26	0.004	0.009	0.004	0.009	0.005	0.011	0.071	
27	0.012	0.026	0.011	0.024	0.014	0.031	0.083	
28	0.005	0.011	0.004	0.009	0.004	0.009	0.066	
29	0.011	0.024	0.011	0.024	0.012	0.026	0.078	0.117
30	0.006	0.013	0.005	0.011	0.006	0.013	0.061	
31	0.011	0.024	0.012	0.026	0.012	0.026	0.073	0.109
32	0.014	0.031	0.015	0.033	0.013	0.029	0.058	
33	0.009	0.020	0.011	0.024	0.011	0.024	0.068	0.102
34	0.005	0.011	0.004	0.009	0.005	0.011	0.054	
35	0.008	0.018	0.011	0.024	0.009	0.020	0.064	0.096
36	0.008	0.018	0.009	0.020	0.008	0.018	0.051	
37	0.021	0.046	0.021	0.046	0.021	0.046	0.061	0.091
38	0.008	0.018	0.008	0.018	0.008	0.018	0.048	
39	0.009	0.020	0.010	0.022	0.008	0.018	0.058	0.087
40	0.003	0.007	0.004	0.009	0.004	0.009	0.046	



SSEG rating per phase (rpp)			5.0/3=1.66 kW				NV=MV*3.68/rpp	
Harmonic	At 100% of rated output						Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps		
2	0.012	0.026	0.036	0.079	0.036	0.079	1.080	
3	0.117	0.258	0.114	0.252	0.106	0.234	2.300	
4	0.005	0.011	0.004	0.009	0.003	0.007	0.430	
5	0.049	0.108	0.045	0.099	0.056	0.124	1.140	
6	0.004	0.009	0.003	0.007	0.003	0.007	0.300	
7	0.037	0.082	0.038	0.084	0.031	0.068	0.770	
8	0.003	0.007	0.004	0.009	0.004	0.009	0.230	
9	0.022	0.049	0.025	0.055	0.030	0.066	0.400	
10	0.004	0.009	0.004	0.009	0.003	0.007	0.184	
11	0.025	0.055	0.025	0.055	0.017	0.038	0.330	
12	0.004	0.009	0.003	0.007	0.003	0.007	0.153	
13	0.021	0.046	0.022	0.049	0.028	0.062	0.210	
14	0.003	0.007	0.003	0.007	0.003	0.007	0.131	
15	0.015	0.033	0.016	0.035	0.012	0.026	0.150	
16	0.002	0.004	0.003	0.007	0.003	0.007	0.115	
17	0.017	0.038	0.017	0.038	0.022	0.049	0.132	
18	0.004	0.009	0.004	0.009	0.004	0.009	0.102	
19	0.014	0.031	0.014	0.031	0.010	0.022	0.118	
20	0.002	0.004	0.004	0.009	0.004	0.009	0.092	
21	0.011	0.024	0.012	0.026	0.016	0.035	0.107	0.160
22	0.002	0.004	0.004	0.009	0.002	0.004	0.084	
23	0.014	0.031	0.013	0.029	0.010	0.022	0.098	0.147
24	0.005	0.011	0.006	0.013	0.004	0.009	0.077	
25	0.012	0.026	0.012	0.026	0.016	0.035	0.090	0.135
26	0.002	0.004	0.004	0.009	0.003	0.007	0.071	
27	0.010	0.022	0.010	0.022	0.008	0.018	0.083	
28	0.002	0.004	0.004	0.009	0.003	0.007	0.066	
29	0.009	0.020	0.008	0.018	0.011	0.024	0.078	0.117
30	0.002	0.004	0.004	0.009	0.003	0.007	0.061	
31	0.008	0.018	0.008	0.018	0.005	0.011	0.073	0.109
32	0.002	0.004	0.004	0.009	0.003	0.007	0.058	
33	0.010	0.022	0.009	0.020	0.011	0.024	0.068	0.102
34	0.002	0.004	0.004	0.009	0.002	0.004	0.054	
35	0.006	0.013	0.005	0.011	0.005	0.011	0.064	0.096
36	0.002	0.004	0.004	0.009	0.003	0.007	0.051	
37	0.012	0.026	0.011	0.024	0.009	0.020	0.061	0.091
38	0.003	0.007	0.005	0.011	0.004	0.009	0.048	
39	0.006	0.013	0.007	0.015	0.006	0.013	0.058	0.087
40	0.003	0.007	0.004	0.009	0.003	0.007	0.046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

--



Power Quality. Harmonics. The requirement is specified in section 5.4.1, test procedure in Annex A or B 1.4.1								
SSEG rating per phase (rpp)				6.0/3=2.0 kW			NV=MV*3.68/rpp	
Harmonic	At 50% of rated output						Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps		
2	0.019	0.035	0.029	0.053	0.031	0.057	1.080	
3	0.097	0.178	0.096	0.177	0.088	0.162	2.300	
4	0.003	0.006	0.004	0.007	0.003	0.006	0.430	
5	0.040	0.074	0.039	0.072	0.049	0.090	1.140	
6	0.003	0.006	0.005	0.009	0.004	0.007	0.300	
7	0.033	0.061	0.034	0.063	0.033	0.061	0.770	
8	0.003	0.006	0.003	0.006	0.003	0.006	0.230	
9	0.023	0.042	0.023	0.042	0.028	0.052	0.400	
10	0.004	0.007	0.004	0.007	0.007	0.013	0.184	
11	0.022	0.040	0.020	0.037	0.023	0.042	0.330	
12	0.005	0.009	0.004	0.007	0.003	0.006	0.153	
13	0.020	0.037	0.019	0.035	0.020	0.037	0.210	
14	0.002	0.004	0.004	0.007	0.003	0.006	0.131	
15	0.014	0.026	0.014	0.026	0.017	0.031	0.150	
16	0.003	0.006	0.003	0.006	0.003	0.006	0.115	
17	0.015	0.028	0.014	0.026	0.017	0.031	0.132	
18	0.003	0.006	0.004	0.007	0.003	0.006	0.102	
19	0.012	0.022	0.013	0.024	0.014	0.026	0.118	
20	0.003	0.006	0.002	0.004	0.003	0.006	0.092	
21	0.010	0.018	0.011	0.020	0.011	0.020	0.107	0.160
22	0.009	0.017	0.009	0.017	0.009	0.017	0.084	
23	0.016	0.029	0.017	0.031	0.017	0.031	0.098	0.147
24	0.011	0.020	0.013	0.024	0.011	0.020	0.077	
25	0.016	0.029	0.014	0.026	0.015	0.028	0.090	0.135
26	0.013	0.024	0.013	0.024	0.011	0.020	0.071	
27	0.009	0.017	0.009	0.017	0.010	0.018	0.083	
28	0.003	0.006	0.003	0.006	0.003	0.006	0.066	
29	0.007	0.013	0.008	0.015	0.009	0.017	0.078	0.117
30	0.003	0.006	0.002	0.004	0.003	0.006	0.061	
31	0.007	0.013	0.007	0.013	0.008	0.015	0.073	0.109
32	0.003	0.006	0.003	0.006	0.004	0.007	0.058	
33	0.010	0.018	0.009	0.017	0.009	0.017	0.068	0.102
34	0.003	0.006	0.002	0.004	0.004	0.007	0.054	
35	0.007	0.013	0.007	0.013	0.007	0.013	0.064	0.096
36	0.002	0.004	0.003	0.006	0.003	0.006	0.051	
37	0.012	0.022	0.010	0.018	0.013	0.024	0.061	0.091
38	0.004	0.007	0.004	0.007	0.003	0.006	0.048	
39	0.007	0.013	0.008	0.015	0.006	0.011	0.058	0.087
40	0.002	0.004	0.003	0.006	0.002	0.004	0.046	



SSEG rating per phase (rpp)			6.0/3=2.0 kW				NV=MV*3.68/rpp	
Harmonic	At 100% of rated output						Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps		
2	0.011	0.020	0.048	0.088	0.041	0.075	1.080	
3	0.140	0.258	0.131	0.241	0.129	0.237	2.300	
4	0.005	0.009	0.008	0.015	0.008	0.015	0.430	
5	0.055	0.101	0.054	0.099	0.063	0.116	1.140	
6	0.007	0.013	0.007	0.013	0.008	0.015	0.300	
7	0.036	0.066	0.035	0.064	0.030	0.055	0.770	
8	0.006	0.011	0.008	0.015	0.008	0.015	0.230	
9	0.019	0.035	0.020	0.037	0.028	0.052	0.400	
10	0.004	0.007	0.005	0.009	0.005	0.009	0.184	
11	0.022	0.040	0.022	0.040	0.014	0.026	0.330	
12	0.006	0.011	0.005	0.009	0.004	0.007	0.153	
13	0.019	0.035	0.018	0.033	0.026	0.048	0.210	
14	0.003	0.006	0.006	0.011	0.006	0.011	0.131	
15	0.014	0.026	0.014	0.026	0.010	0.018	0.150	
16	0.003	0.006	0.005	0.009	0.005	0.009	0.115	
17	0.014	0.026	0.014	0.026	0.019	0.035	0.132	
18	0.004	0.007	0.005	0.009	0.004	0.007	0.102	
19	0.013	0.024	0.012	0.022	0.007	0.013	0.118	
20	0.002	0.004	0.005	0.009	0.004	0.007	0.092	
21	0.011	0.020	0.011	0.020	0.016	0.029	0.107	0.160
22	0.003	0.006	0.005	0.009	0.006	0.011	0.084	
23	0.011	0.020	0.011	0.020	0.006	0.011	0.098	0.147
24	0.004	0.007	0.005	0.009	0.005	0.009	0.077	
25	0.009	0.017	0.010	0.018	0.013	0.024	0.090	0.135
26	0.003	0.006	0.006	0.011	0.005	0.009	0.071	
27	0.010	0.018	0.010	0.018	0.007	0.013	0.083	
28	0.003	0.006	0.005	0.009	0.003	0.006	0.066	
29	0.008	0.015	0.009	0.017	0.011	0.020	0.078	0.117
30	0.004	0.007	0.006	0.011	0.006	0.011	0.061	
31	0.009	0.017	0.008	0.015	0.007	0.013	0.073	0.109
32	0.003	0.006	0.005	0.009	0.004	0.007	0.058	
33	0.010	0.018	0.008	0.015	0.011	0.020	0.068	0.102
34	0.007	0.013	0.006	0.011	0.006	0.011	0.054	
35	0.007	0.013	0.006	0.011	0.005	0.009	0.064	0.096
36	0.002	0.004	0.005	0.009	0.004	0.007	0.051	
37	0.006	0.011	0.006	0.011	0.007	0.013	0.061	0.091
38	0.007	0.013	0.010	0.018	0.007	0.013	0.048	
39	0.007	0.013	0.008	0.015	0.008	0.015	0.058	0.087
40	0.003	0.006	0.006	0.011	0.005	0.009	0.046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

--



Power Quality. Harmonics. The requirement is specified in section 5.4.1, test procedure in Annex A or B 1.4.1								
SSEG rating per phase (rpp)				8.0/3=2.66 kW			NV=MV*3.68/rpp	
Harmonic	At 50% of rated output						Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps		
2	0.021	0.029	0.031	0.039	0.033	0.046	1.080	
3	0.114	0.157	0.111	0.140	0.107	0.148	2.300	
4	0.006	0.008	0.005	0.006	0.005	0.007	0.430	
5	0.031	0.043	0.031	0.039	0.039	0.054	1.140	
6	0.004	0.006	0.004	0.005	0.004	0.006	0.300	
7	0.042	0.058	0.039	0.049	0.040	0.055	0.770	
8	0.003	0.004	0.004	0.005	0.003	0.004	0.230	
9	0.030	0.041	0.032	0.040	0.037	0.051	0.400	
10	0.004	0.006	0.005	0.006	0.005	0.007	0.184	
11	0.031	0.043	0.031	0.039	0.029	0.040	0.330	
12	0.003	0.004	0.005	0.006	0.003	0.004	0.153	
13	0.029	0.040	0.029	0.037	0.032	0.044	0.210	
14	0.003	0.004	0.005	0.006	0.005	0.007	0.131	
15	0.023	0.032	0.023	0.029	0.021	0.029	0.150	
16	0.003	0.004	0.006	0.008	0.004	0.006	0.115	
17	0.023	0.032	0.022	0.028	0.028	0.039	0.132	
18	0.006	0.008	0.006	0.008	0.005	0.007	0.102	
19	0.021	0.029	0.022	0.028	0.017	0.023	0.118	
20	0.005	0.007	0.006	0.008	0.006	0.008	0.092	
21	0.017	0.023	0.018	0.023	0.022	0.030	0.107	0.160
22	0.003	0.004	0.005	0.006	0.003	0.004	0.084	
23	0.015	0.021	0.015	0.019	0.013	0.018	0.098	0.147
24	0.003	0.004	0.005	0.006	0.002	0.003	0.077	
25	0.014	0.019	0.014	0.018	0.017	0.023	0.090	0.135
26	0.003	0.004	0.004	0.005	0.003	0.004	0.071	
27	0.012	0.017	0.012	0.015	0.009	0.012	0.083	
28	0.003	0.004	0.004	0.005	0.002	0.003	0.066	
29	0.010	0.014	0.010	0.013	0.013	0.018	0.078	0.117
30	0.003	0.004	0.004	0.005	0.003	0.004	0.061	
31	0.010	0.014	0.010	0.013	0.008	0.011	0.073	0.109
32	0.003	0.004	0.004	0.005	0.002	0.003	0.058	
33	0.009	0.012	0.009	0.011	0.011	0.015	0.068	0.102
34	0.003	0.004	0.004	0.005	0.003	0.004	0.054	
35	0.008	0.011	0.008	0.010	0.007	0.010	0.064	0.096
36	0.003	0.004	0.004	0.005	0.003	0.004	0.051	
37	0.009	0.012	0.008	0.010	0.010	0.014	0.061	0.091
38	0.003	0.004	0.005	0.006	0.002	0.003	0.048	
39	0.007	0.010	0.008	0.010	0.006	0.008	0.058	0.087
40	0.003	0.004	0.004	0.005	0.002	0.003	0.046	



SSEG rating per phase (rpp)			8.0 /3=2.66kW				NV=MV*3.68/rpp	
Harmonic	At 100% of rated output						Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps		
2	0.017	0.023	0.052	0.072	0.041	0.057	1.080	
3	0.264	0.364	0.246	0.339	0.254	0.351	2.300	
4	0.019	0.026	0.010	0.014	0.013	0.018	0.430	
5	0.042	0.058	0.046	0.063	0.037	0.051	1.140	
6	0.016	0.022	0.010	0.014	0.012	0.017	0.300	
7	0.045	0.062	0.045	0.062	0.044	0.061	0.770	
8	0.011	0.015	0.011	0.015	0.010	0.014	0.230	
9	0.022	0.030	0.028	0.039	0.030	0.041	0.400	
10	0.011	0.015	0.006	0.008	0.008	0.011	0.184	
11	0.028	0.039	0.029	0.040	0.020	0.028	0.330	
12	0.009	0.012	0.005	0.007	0.008	0.011	0.153	
13	0.021	0.029	0.023	0.032	0.029	0.040	0.210	
14	0.008	0.011	0.004	0.006	0.005	0.007	0.131	
15	0.017	0.023	0.018	0.025	0.011	0.015	0.150	
16	0.007	0.010	0.003	0.004	0.007	0.010	0.115	
17	0.016	0.022	0.017	0.023	0.022	0.030	0.132	
18	0.007	0.010	0.004	0.006	0.005	0.007	0.102	
19	0.014	0.019	0.015	0.021	0.011	0.015	0.118	
20	0.007	0.010	0.003	0.004	0.005	0.007	0.092	
21	0.012	0.017	0.013	0.018	0.017	0.023	0.107	0.160
22	0.005	0.007	0.003	0.004	0.004	0.006	0.084	
23	0.012	0.017	0.012	0.017	0.010	0.014	0.098	0.147
24	0.005	0.007	0.003	0.004	0.004	0.006	0.077	
25	0.012	0.017	0.012	0.017	0.013	0.018	0.090	0.135
26	0.005	0.007	0.002	0.003	0.004	0.006	0.071	
27	0.011	0.015	0.011	0.015	0.010	0.014	0.083	
28	0.005	0.007	0.004	0.006	0.004	0.006	0.066	
29	0.010	0.014	0.010	0.014	0.011	0.015	0.078	0.117
30	0.004	0.006	0.003	0.004	0.003	0.004	0.061	
31	0.009	0.012	0.010	0.014	0.009	0.012	0.073	0.109
32	0.004	0.006	0.002	0.003	0.003	0.004	0.058	
33	0.009	0.012	0.010	0.014	0.010	0.014	0.068	0.102
34	0.005	0.007	0.003	0.004	0.004	0.006	0.054	
35	0.008	0.011	0.008	0.011	0.008	0.011	0.064	0.096
36	0.002	0.003	0.003	0.004	0.003	0.004	0.051	
37	0.007	0.010	0.008	0.011	0.007	0.010	0.061	0.091
38	0.016	0.022	0.014	0.019	0.014	0.019	0.048	
39	0.008	0.011	0.008	0.011	0.010	0.014	0.058	0.087
40	0.003	0.004	0.003	0.004	0.003	0.004	0.046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

--



Power Quality. Harmonics. The requirement is specified in section 5.4.1, test procedure in Annex A or B 1.4.1								
SSEG rating per phase (rpp)			10.0/3=3.33 kW				NV=MV*3.68/rpp	
Harmonic	At 50% of rated output						Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps		
2	0.009	0.010	0.048	0.053	0.044	0.049	1.080	
3	0.169	0.187	0.165	0.182	0.161	0.178	2.300	
4	0.004	0.004	0.008	0.009	0.010	0.011	0.430	
5	0.036	0.040	0.031	0.034	0.042	0.046	1.140	
6	0.006	0.007	0.007	0.008	0.007	0.008	0.300	
7	0.042	0.046	0.044	0.049	0.040	0.044	0.770	
8	0.004	0.004	0.007	0.008	0.007	0.008	0.230	
9	0.030	0.033	0.031	0.034	0.039	0.043	0.400	
10	0.004	0.004	0.006	0.007	0.006	0.007	0.184	
11	0.027	0.030	0.028	0.031	0.022	0.024	0.330	
12	0.003	0.003	0.005	0.006	0.004	0.004	0.153	
13	0.025	0.028	0.025	0.028	0.031	0.034	0.210	
14	0.003	0.003	0.006	0.007	0.006	0.007	0.131	
15	0.020	0.022	0.020	0.022	0.016	0.018	0.150	
16	0.003	0.003	0.005	0.006	0.005	0.006	0.115	
17	0.019	0.021	0.019	0.021	0.023	0.025	0.132	
18	0.003	0.003	0.006	0.007	0.005	0.006	0.102	
19	0.017	0.019	0.017	0.019	0.012	0.013	0.118	
20	0.002	0.002	0.005	0.006	0.005	0.006	0.092	
21	0.014	0.015	0.014	0.015	0.019	0.021	0.107	0.160
22	0.002	0.002	0.005	0.006	0.004	0.004	0.084	
23	0.014	0.015	0.013	0.014	0.010	0.011	0.098	0.147
24	0.002	0.002	0.005	0.006	0.004	0.004	0.077	
25	0.012	0.013	0.012	0.013	0.016	0.018	0.090	0.135
26	0.002	0.002	0.004	0.004	0.004	0.004	0.071	
27	0.011	0.012	0.012	0.013	0.008	0.009	0.083	
28	0.002	0.002	0.005	0.006	0.003	0.003	0.066	
29	0.010	0.011	0.009	0.010	0.013	0.014	0.078	0.117
30	0.002	0.002	0.005	0.006	0.004	0.004	0.061	
31	0.009	0.010	0.009	0.010	0.008	0.009	0.073	0.109
32	0.002	0.002	0.005	0.006	0.004	0.004	0.058	
33	0.009	0.010	0.008	0.009	0.010	0.011	0.068	0.102
34	0.002	0.002	0.005	0.006	0.004	0.004	0.054	
35	0.007	0.008	0.007	0.008	0.006	0.007	0.064	0.096
36	0.002	0.002	0.005	0.006	0.004	0.004	0.051	
37	0.007	0.008	0.006	0.007	0.008	0.009	0.061	0.091
38	0.002	0.002	0.006	0.007	0.005	0.006	0.048	
39	0.014	0.015	0.014	0.015	0.014	0.015	0.058	0.087
40	0.002	0.002	0.006	0.007	0.004	0.004	0.046	



SSEG rating per phase (rpp)			10.0/3=3.33kW				NV=MV*3.68/rpp	
Harmonic	At 100% of rated output						Limit in BS EN 61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps	Measured Value (MV) in Amps	Normalised Value (NV) in Amps		
2	0.042	0.046	0.081	0.089	0.050	0.055	1.080	
3	0.413	0.456	0.363	0.401	0.393	0.434	2.300	
4	0.025	0.028	0.016	0.018	0.024	0.026	0.430	
5	0.083	0.092	0.087	0.096	0.077	0.085	1.140	
6	0.017	0.019	0.012	0.013	0.016	0.018	0.300	
7	0.047	0.052	0.044	0.049	0.050	0.055	0.770	
8	0.012	0.013	0.009	0.010	0.011	0.012	0.230	
9	0.019	0.021	0.022	0.024	0.021	0.023	0.400	
10	0.015	0.017	0.012	0.013	0.012	0.013	0.184	
11	0.023	0.025	0.023	0.025	0.019	0.021	0.330	
12	0.008	0.009	0.007	0.008	0.008	0.009	0.153	
13	0.016	0.018	0.017	0.019	0.022	0.024	0.210	
14	0.010	0.011	0.007	0.008	0.008	0.009	0.131	
15	0.012	0.013	0.013	0.014	0.014	0.015	0.150	
16	0.008	0.009	0.006	0.007	0.006	0.007	0.115	
17	0.011	0.012	0.012	0.013	0.017	0.019	0.132	
18	0.008	0.009	0.006	0.007	0.007	0.008	0.102	
19	0.010	0.011	0.011	0.012	0.010	0.011	0.118	
20	0.007	0.008	0.004	0.004	0.007	0.008	0.092	
21	0.010	0.011	0.009	0.010	0.013	0.014	0.107	0.160
22	0.008	0.009	0.007	0.008	0.005	0.006	0.084	
23	0.008	0.009	0.009	0.010	0.006	0.007	0.098	0.147
24	0.006	0.007	0.004	0.004	0.006	0.007	0.077	
25	0.007	0.008	0.008	0.009	0.010	0.011	0.090	0.135
26	0.006	0.007	0.004	0.004	0.005	0.006	0.071	
27	0.007	0.008	0.007	0.008	0.005	0.006	0.083	
28	0.006	0.007	0.005	0.006	0.005	0.006	0.066	
29	0.007	0.008	0.007	0.008	0.008	0.009	0.078	0.117
30	0.004	0.004	0.004	0.004	0.004	0.004	0.061	
31	0.006	0.007	0.007	0.008	0.007	0.008	0.073	0.109
32	0.008	0.009	0.006	0.007	0.008	0.009	0.058	
33	0.007	0.008	0.006	0.007	0.007	0.008	0.068	0.102
34	0.004	0.004	0.004	0.004	0.004	0.004	0.054	
35	0.005	0.006	0.006	0.007	0.006	0.007	0.064	0.096
36	0.004	0.004	0.004	0.004	0.004	0.004	0.051	
37	0.014	0.015	0.016	0.018	0.015	0.017	0.061	0.091
38	0.005	0.006	0.004	0.004	0.004	0.004	0.048	
39	0.005	0.006	0.006	0.007	0.007	0.008	0.058	0.087
40	0.003	0.003	0.003	0.003	0.004	0.004	0.046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.



Power Quality. Voltage fluctuations and Flicker. The requirement is specified in section 5.4.2, test procedure in Annex A or B 1.4.3

	Starting			Stopping			Running	
	d_{max}	d_c	$d_{(t)}$	d_{max}	d_c	$d_{(t)}$	P_{st}	P_{it} 2 hours
Measured Values	0.56%	0.04%	0%	0.56%	0.04%	0%	0.31	0.32
Normalised to standard impedance and 3.68kW for multiple units	NA	NA	NA	NA	NA	NA	NA	NA
Limits set under BS EN 61000-3-3	4%	3.3%	3.3%	4%	3.3%	3.3%	1.0	0.65
Test start date	2017-10-11			Test end date			2017-10-11	
Test location	TÜV Building III, No.177, Lane 777, West Guangzhong Road Zhabei District, Shanghai							

Power quality. DC injection. The requirement is specified in section 5.5, test procedure in Annex A or B 1.4.4

5.0kW			
Test power level	10%	55%	100%
Recorded value	9.4mA	13.2mA	12.0mA
as % of rated AC current	0.13%	0.18%	0.17%
Limit	0.25%	0.25%	0.25%

Power quality. DC injection. The requirement is specified in section 5.5, test procedure in Annex A or B 1.4.4

6.0 kW			
Test power level	10%	55%	100%
Recorded value	9.1mA	21mA	15.7mA
as % of rated AC current	0.10%	0.24%	0.18%
Limit	0.25%	0.25%	0.25%

Power quality. DC injection. The requirement is specified in section 5.5, test procedure in Annex A or B 1.4.4

8.0 kW			
Test power level	10%	55%	100%
Recorded value	27.4mA	11.2mA	18.6mA
as % of rated AC current	0.24%	0.10%	0.16%
Limit	0.25%	0.25%	0.25%



Power quality. DC injection. The requirement is specified in section 5.5, test procedure in Annex A or B 1.4.4				
10.0 kW				
Test power level	10%	55%	100%	
Recorded value	27.8mA	11.8mA	19.3mA	
as % of rated AC current	0.19%	0.8%	0.13%	
Limit	0.25%	0.25%	0.25%	

Power Quality. Power factor. The requirement is specified in section 5.6, test procedure in Annex A or B 1.4.2				
5.0 kW				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.
Measured value	0.998	0.998	0.998	
Limit	>0.95	>0.95	>0.95	

Power Quality. Power factor. The requirement is specified in section 5.6, test procedure in Annex A or B 1.4.2				
6.0 kW				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.
Measured value	0.998	0.998	0.998	
Limit	>0.95	>0.95	>0.95	

Power Quality. Power factor. The requirement is specified in section 5.6, test procedure in Annex A or B 1.4.2				
8.0 kW				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.
Measured value	0.999	0.999	0.999	
Limit	>0.95	>0.95	>0.95	

Power Quality. Power factor. The requirement is specified in section 5.6, test procedure in Annex A or B 1.4.2				
10.0 kW				
	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test.
Measured value	0.999	0.999	0.999	
Limit	>0.95	>0.95	>0.95	



Protection. Frequency tests The requirement is specified in section 5.3.1, test procedure in Annex A or B 1.3.3						
Function	Setting		Trip test		"No-trip tests"	
	Frequency	Time delay	Frequency	Time delay	Frequency /time	Confirm no trip
O/F stage 1	51.5Hz	90s	51.48 Hz	91.0s	51.3Hz 95s	no trip
O/F stage 2	52Hz	0.5s	52.00 Hz	0.508s	51.8Hz 89.98s	no trip
					52.2Hz 0.48s	no trip
U/F stage 1	47.5Hz	20s	47.51 Hz	20.35s	47.7Hz 25s	no trip
U/F stage 2	47Hz	0.5s	47.00 Hz	0.516s	47.2Hz 19.98s	no trip
					46.8 Hz 0.48s	no trip

Protection. Voltage tests The requirement is specified in section 5.3.1, test procedure in Annex A or B 1.3.2						
Function	Setting		Trip test		"No trip-tests" All phases at same voltage	
	Voltage	Time delay	Voltage	Time delay	Voltage /time	Confirm no trip
O/V stage 1	262.2V	1.0s	261.1V	1.01s	258.2V 2.0 s	no trip
O/V stage 2	273.7V	0.5s	272.4V	0.508s	269.7V 0.98s	no trip
					277.7V 0.48s	no trip
U/V stage 1	200.1V	2.5s	200.0V	2.52s	204.1V 3.5s	no trip
U/V stage 2	184V	0.5s	183.9V	0.508s	188V 2.48s	no trip
					180v 0.48 sec	no trip

Note. For voltage tests the voltage required to trip is the setting plus or minus 3.45V. The time delay can be measured at a larger deviation than the minimum required to operate the projection. The No-trip tests need to be carried out at the setting $\pm 4V$ and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

Protection. Loss of Mains test. The requirement is specified in section 5.3.2, test procedure in Annex A or B 1.3.4						
Note as an alternative, inverters can be tested to BS EN 62116. The following sub set of tests should be recorded in the following table.						
Test Power and imbalance	33% -5% Q Test 22	66% -5% Q Test 12	100% -5% P Test 5	33% +5% Q Test 31	66% +5% Q Test 21	100% +5% P Test 10
Trip time. Limit is 0.5s	1.845s	0.237s	0.372s	0.796s	0.203s	0.290s



Protection. Frequency change, Stability test The requirement is specified in section 5.3.3, test procedure in Annex A or B 1.3.6

	Start Frequency	Change	End Frequency	Confirm no trip
Positive Vector Shift	49.5Hz	+9 degrees		no trip
Negative Vector Shift	50.5Hz	- 9 degrees		no trip
Positive Frequency drift	49.5Hz	+0.19Hz/s	51.5Hz	no trip
Negative Frequency drift	50.5Hz	-0.19Hz/s	47.5Hz	no trip

Protection. Re-connection time. The requirement is specified in section 5.3.4, test procedure in Annex A or B 1.3.5

Test should prove that the reconnection sequence starts after a minimum delay of 20 seconds for restoration of voltage and frequency to within the stage 1 settings of table 1.

Time delay setting	Measure d delay	Checks on no reconnection when voltage or frequency is brought to just outside stage 1 limits of table 1.			
60s	71.6s	At 266.2V	At 196.1V	At 47.4Hz	At 51.6Hz
Confirmation that the SSEG does not re-connect.		No-reconnection	No-reconnection	No-reconnection	No-reconnection

Fault level contribution. The requirement is specified in section 5.7, test procedure in Annex A or B 1.4.6

For a directly coupled SSEG			For a Inverter SSEG		
Parameter	Symbol	Value	Time after fault	Volts	Amps
Peak Short Circuit current	i_p	NA	20ms	32.87V	1.78A
Initial Value of aperiodic current	A	NA	100ms	27.94V	0.06A
Initial symmetrical short-circuit current*	I_k	NA	250ms	27.92V	0.06A
Decaying (aperiodic) component of short circuit current*	i_{DC}	NA	500ms	27.92V	0.06A
Reactance/Resistance Ratio of source*	X/R	NA	Time to trip	22ms	In seconds

Self-Monitoring solid state switching The requirement is specified in section 5.3.1, No specified test requirements.

5.0 / 6.0 / 8.0 / 10kW	NA
It has been verified that in the event of the solid state switching device failing to disconnect the SSEG, the voltage on the output side of the switching device is reduced to a value below 50 volts within 0.5 seconds.	

Additional comments

--